

KTLD-30-UV-SC1050-56-VDIM-U7 CONSTANT CURRENT PROGRAMMABLE LED DRIVER

DESCRIPTION

LED Driver | 30W | 120–277V Input | 350–1050mA Programmable Output Current

TOTAL POWER: 30W	OUTPUT CURRENT: 350–1050mA
INPUT VOLTAGE: 120-277Vac ±10%	DIMMING: 0-10V
INPUT FREQUENCY: 50/60 Hz	WARRANTY: 5 Years

PRODUCT FEATURES

- Meets FCC Part 15 (Class B) consumer limits
- Short circuit overload and open load protection
- Dimmable with 0–10V dimmer (down to 1% at max. output current)
- Auxiliary Power: 12Vdc; 200mA max.
- THD: <20%

PROGRAMMING FEATURES

- Drive current (10mA increments)
- Minimum dimming level (1%, 3%, 5%, 7%, or 10%)
- Dimming curve (linear, log, inverse log, or square-law)
- Minimum dimming voltage (1V, 1.5V, or 2V)
- Maximum dimming voltage (7V, 8V, or 9V)
- Dim-to-off voltage (0.8V, 1V, 1.2V, or N/A)
- Thermal foldback temperature (167°F [75°C], 176°F [80°C], 185°F [85°C], or 194°F [90°C])

• -4°F (20°C) to 122°F (50°C) operating temperature

- 194°F (90°C) maximum case temperature
- Input frequency: 50/60 Hz
- Programmable output current via Keystone supplied
- Programming jig

WHAT'S NEEDED? A SmartCurrent Programmable LED Driver, the SmartCurrent Cradle, and a computer.



ELECTRICAL SPECIFICATIONS

Input Voltage Range	120-277Vac ±10%
Frequency	50/60 Hz
Power Factor	>0.9 under 120~277Vac Input with 80~100% load condition (for all output currents)
Inrush Current	10A @120V
Max. Input Current	0.31A @120V, 0.17A @240V, and 0.15A @277V
THD	<20% under 120~277Vac input with 80~100% load condition (for all output currents)
Load Regulation	± 2%
Line Regulation	±1%
Output Tolerance	± 5% at full load condition
Turn-On Delay Time	<2 seconds at full load condition
Overshoot	<10% at full load condition
No Load Power Consumption	<1.5W
Ripple and Noise (pk-pk)	<3%
Withstand Voltage	Input to output, 2,800Vdc, 2mA
Leakage Current	Maximum 0.5mA at 277Vac, 60Hz input
Protection	 Over Voltage Protection: Hiccup mode. Protection will trigger when load voltage exceeds specified output voltage and will auto recover after the fault mode is removed. Over Current Protection: Hiccup mode. Protection will trigger when load current exceeds specified output current and will auto recover after the fault mode is removed. Short Circuit Protection: Hiccup mode. Protection will trigger when short circuit and will auto recover after the fault mode is removed. Short Circuit Protection: Protection will trigger when driver overheats and auto-recovery when cooled down.








KTLD-30-UV-SC1050-56-VDIM-U7

CONSTANT CURRENT PROGRAMMABLE LED DRIVER


PRODUCT SPECIFICATIONS

Max. Output Power	Output Current	Output Voltage	OCV	Typical Efficiency at 120V	Typical Efficiency at 240V	Typical Efficiency at 277V	Remote Mounting Distance (#18 AWG)		lass 2
Fower				1204	2401	2///	Distance (#10 AWG)	US	Canada
30W	350–1050mA	10-56V	60V		84%@ 1.05A, 29Vdc 82%@ 0.35A, 56Vdc		35 ft.	1	


PHYSICAL SPECIFICATIONS



TOP VIEW




FRONT VIEW



SIDE VIEW



WIRING SPECIFICATIONS







KTLD-30-UV-SC1050-56-VDIM-U7 CONSTANT CURRENT PROGRAMMABLE LED DRIVER


ENVIRONMENTAL SPECIFICATIONS

SAFETY AND EMC COMPLIANCE

Operating Temperature	-4 to 122°F (-20 to 50°C)	UL/cUL
Storage Temperature	-40 to 185°C (-40 to 85°C)	CE
Humidity	5% to 95%	FCC, 47CFR Part
MTBF	397,500 hours at 104°F (40°C) ambient (~94°F [~70°C] case temp)	
Life Rating	85,000 hours at 120Vac input, 100% load and 140°F (60°C) case temperature	EN61000-3-2
Maximum Case Temperature	194°F (90°C)	

UL/cUL	UL 8750, Class P, Type HL
CE	EN61347-1, EN61347-2-13
FCC, 47CFR Part 15	ANSI C63.4:2009 Class B (consumer limit)
EN61000-3-2	Harmonic Current Emissions Class C

LED DRIVER OUTPUT WINDOW



Note: driver is in constant power mode from 550mA to 1050mA.

ORDERING INFORMATION

ORDER CODE	PACKAGING STYLE	PACK QUANTITY	ITEM STATUS
KTLD-30-UV-SC1050-56-VDIM-U7-CP	Carton Pack	TBD	Quick Ship

CATALOG NUMBER BREAKDOWN

UV-SC1050-56-VDI ЦL L Т Т Keystone Technologies Max. Output 120-277V Smart Max. Output 0-10V Dimming Max. Output Case Style Packaging LED Driver Input Style Wattage Current Voltage Current