

6" LED Emergency Recessed Can Retrofit Kit

LED.

50,000 Hours Life, 12Watt, 120VAC

Applications:

6" Recessed Can Kit, Indoor And Damp Locations Use



2700K SOFT WARM WHITE 3000K WARM WHITE 3500K BRIGHT WARM WHITE 4000K COOL WHITE 5000K DAY LIGHT

Features:

- Adjustable 5 Color 2700K, 3000K, 3500K, 4000K and 5000K
- Replace Incandescent Save 80% Energy (100 Watt Equivalent)
- Smooth Dimming to 10% or Below
- Dims on Most Standard Household Dimmers
- Fits Standard 6 Inch Recess Cans
- Comes with Standard Quick Connect Plug
- High Efficacy 90CRI True Color
- Used As A Normal Lamp & If The Power Goes Out It Switches to Battery Power on Its Own (2-in-1 Function)
- Operates 2 Hours During Power Outage
- If Lamp Was Not Turned on and Household Power Failed, Just Switch Wall Switch on and Unit Will Operate on Battery Power





Specification:

Input Line Voltage:	120VAC		
Input Power			
Input Line Frequency	60Hz		
	50,000hrs		
	-20°C/-4°F		
Maximum Operating Temp	40°C/104°F		
Adjustable CCT			
	≥90		
	1000		
Doom Angle	110°		
CBCP			
Dimmable	Standard Triac Dimmer		



WARRANTY
2-YEAR*

Model:#	Description	wattage	lumens	Socket
LC12RT6-B-CCTBK	6 Inch Dimmable, Baffled Retrofit Can Kit 5CCT with Battery Backup Function	12W	1000	E26

^{* 2} Year Limited Warranty

Note: Emergency works best without dimmer switch.

May not operate on all dimmers.

UPC: 74616080074-5

